

VIGOR VS-4TC Thermocouple Temperature Input Module


Forward

The VS-4TC Thermocouple Temperature Input Module can receive external 4 channels of thermocouple (TC) signals and convert those into digital temperature values. When the FROM instruction is executed, the VS Main Unit reads out temperature data from the VS-4TC module and stores that into registers. Thus, it provides the reference data for digital monitoring and related controls.

Since the conversion circuit for those input channels is not divided, the isolated (ungrounded) thermocouple sensors and reducing interference are required.

The VS-4TC Thermocouple Temperature Input Module requires a DC 24V external power input for the isolated DC to DC regulated power to provide its temperature converter. Also, between the PLC inner circuit and the converter are isolated by the Magnetic-coupler thus the module can get a stable temperature conversion. Please read following instructions before use.

Component Designation



Specification

Temperature Input Specification

Item	Specification
Sensor Type	K, J, R, S, T, E, B or N type isolated (ungrounded) thermocouple
Measurable Range	K: -200 °C ~ 1200 °C (-328 °F ~ 2192 °F)
	J: -160 °C ~ 1200 °C (-256 °F ~ 2192 °F)
	R: 0 °C ~ 1768 °C (32 °F ~ 3214.4 °F)
	S: 0 °C ~ 1768 °C (32 °F ~ 3214.4 °F)
	T: -220 °C ~ 400 °C (-364 °F ~ 752 °F)
	E: -220 °C ~ 1000 °C (-364 °F ~ 1832 °F)
	B: 300 °C ~ 1800 °C (572 °F ~ 3272 °F)
Converted Value	N: -200 °C ~ 1300 °C (-328 °F ~ 2372 °F)
	The measurement results are indicated by the unit of 0.1 °C or 0.1 °F
Resolution	0.1 °C (0.1 °F)
Overall Accuracy	±0.5 % (full scale.) ±1 °C
Response Time	500 ms

Basic Specification

Item	Specification
Isolation Method	The external DC 24V input through an isolated DC/DC power to provide temp. convert circuits; Magnetic-coupler isolation between PLC and temperature converters; No isolation between input channels (ungrounded thermocouple is required)
Power Consumption	DC 24V ± 20%, 30mA (Max.) from external + DC 5V 15mA from PLC's inner power

Definition of Buffer Memory BFM in the VS-4TC Module

The VS-4TC module uses the BFMs to communicate with the VS Main Unit for the parameter setting and converted value access.

BFM No.	Component Description
#0	To assign the thermocouple types for TC1~TC4. When the power is turned from OFF to ON, the default value is H0000.
#2	To assign the scale of temperature measurement. 0: °C ; 1: °F ; other values: °C . When the power is turned from OFF to ON, the default value is 0.
#3	To set the average times of TC1.
#4	To set the average times of TC2.
#5	To set the average times of TC3.
#6	To set the average times of TC4.
#11	Converted temperature value of TC1, with unit as 0.1 °C or 0.1 °F .
#12	Converted temperature value of TC2, with unit as 0.1 °C or 0.1 °F .
#13	Converted temperature value of TC3, with unit as 0.1 °C or 0.1 °F .
#14	Converted temperature value of TC4, with unit as 0.1 °C or 0.1 °F .
#29	Status and error flag.
#30	Identification code: VS-4TC = K205 (can use the FROM instruction to check whether the place is this module or not)
#31	The version number of this module. (the content value XX indicates Ver. X.X)


BFM #0 To appoint the types of thermocouples:

b15	BFM#0				b0	Value of Nibble								Thermocouple Type								If Value of Nibble is not 0~7, the channel is disabled.							
Nibble #4	Nibble #3	Nibble #2	Nibble #1			0	1	2	3	4	5	6	7	K	J	R	S	T	E	B	N								
TC4	TC3	TC2	TC1																										


Example: If the BFM #0 of a VS-4TC is set to be H8100, then

TC1 & TC2: K Type thermocouple input;
TC3: J Type thermocouple input; TC4: disabled.

BFM #29 Status and Error Flag: (0: normal; 1: error)



External Wiring



*1: Always use isolated (ungrounded) thermocouple sensor.

*2: Please use the shield isolation cable for every temperature input, and keep the signal cable away from power lines to minimize external interference.

*3: Please connect the end of cable shield to the FG terminal. If the noise is huge, should connect the FG to the Main Unit.

*4: Please use appropriate compensating cables for thermocouple extension.

Example Program

The VS-4TC is installed next to the Main Unit and became the 1st. special module. Its TC1~TC2 are used for K type thermocouples, TC3~TC4 are used for J type thermocouples. Temperature converted values of TC1~TC4 are sequentially stored at D100~D103.

